

100Gb/s QSFP28 ZR4 100KM Transceiver HX4X-CL3W1C

Features

- Compliant with 100GBASE-ZR4
- Support line rates 103.125 Gb/s
- Built-in 4-channel Clock and Data Recovery (CDR) in TX and RX
- LAN WDM EML laser and PIN receiver with SOA
- Up to 100km reach for G.652 SMF
- Hot pluggable 38 pin electrical interface
- QSFP28 MSA compliant
- Duplex LC optical receptacle
- RoHS-10 compliant and lead-free
- Excellent EMI performance
- Single +3.3V power supply
- Maximum power consumption 5.5W
- Case operating temperature
 Commercial: 0 ~ 70°C



Applications

- 100GBASE-ZR4 Ethernet Links
- Infiniband QDR and DDR interconnects
- Telecom networking

Part Number Ordering Information

Part Number	Data Rate (Gb/s)	Wavelength (nm)	Transmission Distance(km)	Temperature (°C) (Operating Case)
HX4X-CL3W1C	103.1	1295.56, 1300.05, 1304.58, 1309.14	100	0~70

I. Absolute Maximum Ratings

It has to be noted that the operation in excess of any individual absolute maximum ratings might



cause permanent damage to this module.

Parameter	Symbol	Min	Max	Unit	Notes
Storage Temperature	T_{S}	-40	85	°C	
Power Supply Voltage	V_{CC}	-0.3	4.0	V	
Relative Humidity (non-condensation)	RH	15	85	%	
Damage Threshold	TH_{d}	6.5		dBm	

II. Recommended Operating Conditions

Parameter	Symbo 1	Min	Typical	Max	Unit	Notes
		0		70	°C	Commercial
Operating Case Temperature	T_{OP}	-5		85	°C	Extended
		-40		85	°C	Industrial
Power Supply Voltage	V_{CC}	3.135	3.3	3.465	V	
Data Rate, each Lane			25.78125	28.05	Gb/s	
Control Input Voltage High		2		Vcc	V	
Control Input Voltage Low		0		0.8	V	
Link Distance (SMF)	D			100	km	1

Notes:

1. Depending on actual fiber loss/km (link distance specified is for fiber insertion loss of 0.35dB/km)

III. General Description

Walsun'HX4X-CL3W1C is designed for 100km optical communication applications. This module contains 4-lane optical transmitter, 4-lane optical receiver and module management block including 2 wire serial inter-face. The optical signals are multiplexed to a single-mode fiber through an industry standard LC connector. A block diagram is shown in Figure 1.

ModSelL

The ModSelL is an input pin. When held low by the host, the module responds to 2-wire serial communication commands. The ModSelL allows the use of multiple modules on a single 2-wire interface bus. When the ModSelL is "High", the module shall not respond to or acknowledge any 2-wire interface communication from the host. ModSelL signal input node shall be biased to the "High" state in the module.

In order to avoid conflicts, the host system shall not attempt 2-wire interface communications within the ModSelL de-assert time after any modules are deselected. Similarly, the host shall wait at least for the period of the ModSelL assert time before communicating with the newly selected module. The assertion and de-asserting periods of different modules may overlap as long as the



above timing requirements are met.

Transceiver Block Diagrams




Figure 1. Transceiver Block Diagram

ResetL:

The ResetL pin shall be pulled to Vcc in the module. A low level on the ResetL pin for longer than the minimum pulse length (t_Reset_init) initiates a complete module reset, returning all user module settings to their default state. Module Reset Assert Time (t_init) starts on the rising edge after the low level on the ResetL pin is released. During the execution of a reset (t_init) the host shall disregard all status bits until the module indicates a completion of the reset interrupt. The module indicates this by asserting "low" an IntL signal with the Data Not_Ready bit negated. Note that on power up (including hot insertion) the module should post this completion of reset interrupt without requiring a reset.

LPMode:

LPMode: The LPMode pin shall be pulled up to Vcc in the module. The pin is a hardware control used to put modules into a low power mode when high. By using the LPMode pin and a combination of the Power override, Power_set and High_Power_Class_Enable software control bits (Address A0h, byte 93 bits 0,1,2).

ModPrsL:

ModPrsL is pulled up to Vcc_Host on the host board and grounded in the module. The ModPrsL is asserted "Low" when inserted and deasserted "High" when the module is physically absent from the host connector.

IntL:

IntL is an output pin. When IntL is "Low", it indicates a possible module operational fault or a



status critical to the host system. The host identifies the source of the interrupt using the 2-wire serial interface. The IntL pin is an open collector output and shall be pulled to host supply voltage on the host board. The INTL pin is deasserted "High" after completion of reset, when byte 2 bit 0 (Data Not Ready) is read with a value of '0' and the flag field is read.

IV. Pin Assignment and Pin Description




Figure 2. Diagram of host board connector block pin numbers and names

Pin	Symbol	Name/Description	Notes
1	GND	Transmitter Ground (Common with Receiver Ground)	1
2	Tx2n	Transmitter Inverted Data Input	
3	Tx2p	Transmitter Non-Inverted Data Input	
4	GND	Transmitter Ground (Common with Receiver Ground)	1
5	Tx4n	Transmitter Inverted Data Input	
6	Tx4p	Transmitter Non-Inverted Data Input	
7	GND	Transmitter Ground (Common with Receiver Ground)	1
8	ModSelL	Module Select	
9	ResetL	Module Reset	



10 VccRx 3.3V Power Supply Receiver 2 11 SCL 2-Wire serial Interface Clock 12 SDA 2-Wire serial Interface Data 13 GND Transmitter Ground (Common with Receiver Ground) 14 Rx3p Receiver Non-Inverted Data Output 15 Rx3n Receiver Inverted Data Output 16 GND Transmitter Ground (Common with Receiver Ground) 1 17 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 1 20 GND Transmitter Ground (Common with Receiver Ground) 1 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 1 24 Rx4n Receiver Non-Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 1 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 GND Transmitter Ground (Common with Receiver Ground) 1 10 Transmitter Ground (Common with Receiver Ground) 1 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 30 Vcc1 3.3V power supply transmitter 30 Vcc1 3.3V power supply Transmitter 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Ground (Common with Receiver Ground) 1			W	
12 SDA 2-Wire serial Interface Data 13 GND Transmitter Ground (Common with Receiver Ground) 14 Rx3p Receiver Non-Inverted Data Output 15 Rx3n Receiver Inverted Data Output 16 GND Transmitter Ground (Common with Receiver Ground) 1 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 1 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 1 Rx4n Receiver Inverted Data Output 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 30 Vcc1 3.3V power supply 2 1 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	10	VccRx	3.3V Power Supply Receiver	2
13 GND Transmitter Ground (Common with Receiver Ground) 14 Rx3p Receiver Non-Inverted Data Output 15 Rx3n Receiver Inverted Data Output 16 GND Transmitter Ground (Common with Receiver Ground) 17 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 30 Vcc1 3.3V power supply 21 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 21 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 23 Tx3p Transmitter Non-Inverted Data Input	11	SCL	2-Wire serial Interface Clock	
14 Rx3p Receiver Non-Inverted Data Output 15 Rx3n Receiver Inverted Data Output 16 GND Transmitter Ground (Common with Receiver Ground) 17 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 0 Vcc1 3.3V power supply 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	12	SDA	2-Wire serial Interface Data	
15 Rx3n Receiver Inverted Data Output 16 GND Transmitter Ground (Common with Receiver Ground) 17 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 GND Transmitter Ground (Common with Receiver Ground) 30 Vcc1 3.3V power supply 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	13	GND	Transmitter Ground (Common with Receiver Ground)	
16 GND Transmitter Ground (Common with Receiver Ground) 17 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 Vcc1 3.3V power supply 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	14	Rx3p	Receiver Non-Inverted Data Output	
17 Rx1p Receiver Non-Inverted Data Output 18 Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 Vcc1 3.3V power supply 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	15	Rx3n	Receiver Inverted Data Output	
Rx1n Receiver Inverted Data Output 19 GND Transmitter Ground (Common with Receiver Ground) 20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 Vcc1 3.3V power supply 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	16	GND	Transmitter Ground (Common with Receiver Ground)	1
19 GND Transmitter Ground (Common with Receiver Ground) 1 20 GND Transmitter Ground (Common with Receiver Ground) 1 Rx2n Receiver Inverted Data Output 2 Rx2p Receiver Non-Inverted Data Output 2 GND Transmitter Ground (Common with Receiver Ground) 1 Rx4n Receiver Inverted Data Output 1 Rx4n Receiver Inverted Data Output 2 Rx4p Receiver Non-Inverted Data Output 2 GND Transmitter Ground (Common with Receiver Ground) 1 ModPrsl Module Present 2 IntL Interrupt 2 VccTx 3.3V power supply transmitter 2 Vcc1 3.3V power supply 3 LPMode Low Power Mode 3 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	17	Rx1p	Receiver Non-Inverted Data Output	
20 GND Transmitter Ground (Common with Receiver Ground) 21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 y Vcc1 3.3V power supply 2 1 1 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	18	Rx1n	Receiver Inverted Data Output	
21 Rx2n Receiver Inverted Data Output 22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 29 VccTx 3.3V power supply 30 Vccl 3.3V power supply 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground) 1 Transmitter Ground (Common with Receiver Ground)	19	GND	Transmitter Ground (Common with Receiver Ground)	1
22 Rx2p Receiver Non-Inverted Data Output 23 GND Transmitter Ground (Common with Receiver Ground) 24 Rx4n Receiver Inverted Data Output 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 20 Vcc1 3.3V power supply 21 JLPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 33 Tx3p Transmitter Non-Inverted Data Input	20	GND	Transmitter Ground (Common with Receiver Ground)	1
23 GND Transmitter Ground (Common with Receiver Ground) 1 24 Rx4n Receiver Inverted Data Output 1 25 Rx4p Receiver Non-Inverted Data Output 2 26 GND Transmitter Ground (Common with Receiver Ground) 1 27 ModPrsl Module Present 2 28 IntL Interrupt 2 29 VccTx 3.3V power supply transmitter 2 30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 3 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	21	Rx2n	Receiver Inverted Data Output	
24 Rx4n Receiver Inverted Data Output 1 25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 1 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	22	Rx2p	Receiver Non-Inverted Data Output	
25 Rx4p Receiver Non-Inverted Data Output 26 GND Transmitter Ground (Common with Receiver Ground) 1 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	23	GND	Transmitter Ground (Common with Receiver Ground)	1
26 GND Transmitter Ground (Common with Receiver Ground) 1 27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	24	Rx4n	Receiver Inverted Data Output	1
27 ModPrsl Module Present 28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 30 Vccl 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	25	Rx4p	Receiver Non-Inverted Data Output	
28 IntL Interrupt 29 VccTx 3.3V power supply transmitter 2 30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	26	GND	Transmitter Ground (Common with Receiver Ground)	1
29 VccTx 3.3V power supply transmitter 2 30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	27	ModPrsl	Module Present	
30 Vcc1 3.3V power supply 2 31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	28	IntL	Interrupt	
31 LPMode Low Power Mode 32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	29	VccTx	3.3V power supply transmitter	2
32 GND Transmitter Ground (Common with Receiver Ground) 1 33 Tx3p Transmitter Non-Inverted Data Input	30	Vcc1	3.3V power supply	2
33 Tx3p Transmitter Non-Inverted Data Input	31	LPMode	Low Power Mode	
	32	GND	Transmitter Ground (Common with Receiver Ground)	1
3/1 Tv3n Transmitter Inverted Data Input	33	Tx3p	Transmitter Non-Inverted Data Input	
1731 Transmitter inverted Data input	34	Tx3n	Transmitter Inverted Data Input	



35	GND	Transmitter Ground (Common with Receiver Ground)	1
36	Tx1p	Transmitter Non-Inverted Data Input	
37	Tx1n	Transmitter Inverted Data Input	
38	GND	Transmitter Ground (Common with Receiver Ground)	1

Notes:

- 1. GND is the symbol for signal and supply (power) common for QSFP28 modules. All are common within the QSFP28 module and all module voltages are referenced to this potential unless otherwise noted. Connect these directly to the host board signal common ground plane.
- 2. VccRx, Vcc1 and VccTx are the receiving and transmission power suppliers and shall be applied concurrently. Recommended host board power supply filtering is shown below. Vcc Rx, Vcc1 and Vcc Tx may be internally connected within the QSFP28 transceiver module in any combination. The connector pins are each rated for a maximum current of 1000mA.




Figure 2. RECOMMENDED HOST BOARD POWER SUPPLY FILTERING

V. Electrical Characteristics

The following electrical characteristics are defined over the Recommended Operating



Environment unless otherwise specified.

Parameter	Symbol	Min.	Тур.	Max	Unit	Notes			
Power Consumption	p			5.5	W				
Supply Current	Icc			1585	mA				
Transmitter (each Lane)									
Input differential impedance Rin 100 Ω									
Differential Termination Mismatch				10	%				
Differential Data Input Amplitude	Vin, PP	180		1000	mV				
	VIL	-0.3		0.8	V				
LPMode, Reset and ModSelL	Vih	2		Vcc+0.3	V				
	R	eceiver							
Differential Data Output Amplitude	Vout, PP	350		900	mV				
Differential Termination Mismatch				10	%				
Transition Time, 20 to 80%		9.5			ps				
	Vol	0		0.4	V				
ModPrsL and IntL	Vон	Vcc-0.5		Vcc+0.3	V				

VI. Optical Characteristics

The following optical characteristics are defined over the Recommended Operating Environment unless otherwise specified.

Parameter	Symbol	Min.	Typical	Max	Unit	Notes		
Transmitter								
	L0	1294.53	1295.56	1296.59	nm			
	L1	1299.02	1300.05	1301.09	nm			
Lane wavelength (range)	L2	1303.54	1304.58	1305.63	nm			
	L3	1308.09	1309.14	1310.09	nm			
Signaling rate, each lane			25.78125		Gb/s			
Side-mode suppression	SMSR	30						



			W			
ratio						
Total launch power	PT	8.0		12	dBm	
Average launch power, each lane	Pavg	2.0		6	dBm	
Extinction Ratio	ER	6.0			dB	
Difference in Launch Power between any Two Lanes (OMA)	Ptx,diff			3.6	dB	
Average launch power of OFF transmitter, each lane	Poff			-30	dBm	
Transmitter reflectance	R_{T}			-12	dB	
RIN ₂₀ OMA	RIN			-130	dB/Hz	
Optical Return Loss Tolerance	TOL			20	dB	
Transmitter eye mask {X1, X2, X3, Y1, Y2, Y3}		{0.25, 0.4	1, 0.45, 0.25, 0	0.28, 0.4}		
	_	Receiver				
Signaling rate, each lane			25.78125		Gb/s	
Average Receive Power, each Lane		-30		-7	dBm	
Input Saturation Power, each Lane				-7	dBm	
Receiver reflectance				-26	dB	
Receiver sensitivity	SEN1			-24	dBm	1
Average, each lane	SEN2			-30	dBm	2
LOS Assert	LOSA	-40			dBm	
LOS Deassert	LOSD			-31	dBm	
LOS Hysteresis	LOSH	0.5			dB	

Notes:

- 1. Measured @25.78125Gbps, ER=8.2dB, BER=<1E-12, PRBS=2^31-1
- 2. Measured @25.78125Gbps, ER=8.2dB, BER=<5E-5, PRBS=2^31-1

VII. Digital Diagnostic Functions



The following digital diagnostic characteristics are defined over the normal operating conditions unless otherwise specified.

Parameter	Symbol	Min.	Max	Unit	Range
Temperature monitor absolute error	DMI_ Temp	-3	3	°C	0~85C
Supply voltage monitor absolute error	DMI_VCC	-3	3	%	0~Vcc
RX power monitor absolute error	DMI_RX	-3	3	dВ	-7~-30dBm
Bias current monitor error	DMI_ bias	-10	10	%	0~100mA
TX power monitor absolute error	DMI_TX	-3	3	dB	1∼6dBm

VIII. Mechanical Dimensions




Figure 3. Mechanical Outline



IX. Revision History

Version No.	Initiated	Revised contents	Release Date
V1.0	Andy Zhang	Preliminary datasheet	2021-10-20
V1.1	Andy Zhang	Update the spec of TX power	2022-10-22

X. Contact us

Walsun Optics Technology Co., Ltd

2-5# Tongfufu Industrial Zone, Aiqun Road, Shiyan Street, Baoan District, Shenzhen, China

T. +86 0755-23007456 F. +86 0755-23007451 PC. 518108

E. sales@walsun.com H. www.walsun.com